

Pyramid Series Control Cards

The following control cards are currently available:

Control Card	Description	1 Beep	2 Beeps
Advanced Pyramid Proximity Features			
fleaPower™	Toggles between the fleaPower low-power eco-technology mode and the normal operational mode.	fleaPower is disabled	fleaPower is enabled
Tamper Mode	Toggles between normal operation and the tamper mode for Wiegand output only. Output 8 data bits approximately once every minute.	Tamper Mode is disabled	Tamper Mode is enabled
MAXSecure™ Code	Locks the reader to a specific MAXSecure code setting. In the MAXSecure mode, the reader will read and transmit credential data only from those credentials that provide a security handshake code that matches the specific security handshake code provided to the reader by the MAXSecure control card.	3-beeps when finished	
Installation Tools			
Data Line Test	Initiates a test verifying the reader's ability to transmit data to the access panel, as well as verifying the continuity of the data connecting the reader to the access panel.	Data Line Test is disabled	Data Line Test is enabled
Factory Default	Restores reader to factory default settings.	3-beeps when finished	
Hold Mode	Toggles between normal operation and the hold line mode. A reader in the hold line mode will output the data of the last card read when the hold line is pulled low.	Hold Mode is disabled	Hold Mode is enabled
LED Mode	Toggles the reader between single line and dual line reader LED operation. Single line LED operation is the factory default setting.	1 line LED control	2 line LED control

Reference Table

Pyramid Series



Pyramid Series Control Cards

Reference Table

Pyramid Series

Control Card	Description	1 Beep	2 Beeps
Installation Tools (continued)			
Non-Stop Output	Toggles the reader between normal operation and outputting data approximately once per second, as long as the credential is within the reader's read range.	Non-Stop is disabled	Non-Stop is enabled
Field Customization			
Beeper Suppress	Toggles the reader between normal operation and not beeping during "Beep-n-Flash". Normally the reader will automatically sound the beeper after card presentation.	QuickBeep is disabled	QuickBeep is enabled
LED Suppress	Toggles the reader between normal operation and not flashing its LED during "Beep-N-Flash". Normally the reader will automatically flash its LED after card presentation.	QuickFlash is disabled	QuickFlash is enabled
Magnetic Stripe Format Lock	Locks the reader data transfer format to magnetic stripe format only. Normally the reader will transfer data in the format of the presented credential.	N/A	Locks to Magstripe
Wiegand Format Lock	Locks the reader data transfer format to Wiegand format only. Normally the reader will transfer data in the format of the presented credential.	N/A	Locks to Wiegand
Wiegand Keypad Data Mode	Toggles between 8-bit burst and 26-bit Wiegand data transmission modes (this control card is only used with the proximity reader and keypad devices).	4-beeps special mode	